

(Autonomous) (ISO/IEC - 27001 - 2013 Certified)

WINTER-18 EXAMINATION

Subject Name: Advanced Surveying Model Answer

Subject Code:

17419

Important Instructions to examiners:

- 1) The answers should be examined by key words and not as word-to-word as given in the model answer scheme.
- 2) The model answer and the answer written by candidate may vary but the examiner may try to assess the understanding level of the candidate.
- 3) The language errors such as grammatical, spelling errors should not be given more Importance (Not applicable for subject English and Communication Skills.
- 4) While assessing figures, examiner may give credit for principal components indicated in the figure. The figures drawn by candidate and model answer may vary. The examiner may give credit for any equivalent figure drawn.
- 5) Credits may be given step wise for numerical problems. In some cases, the assumed constant values may vary and there may be some difference in the candidate's answers and model answer.
- 6) In case of some questions credit may be given by judgement on part of examiner of relevant answer based on candidate's understanding.
- 7) For programming language papers, credit may be given to any other program based on equivalent concept.

Q. No.	Sub Q.N.	Answer	
Q.1	a)	Attempt any <u>SIX</u> of the following	(12)
	(i) Ans.	Define contour interval and horizontal equivalent. Contour interval The vertical distance between two successive contours is called "Contour Interval". Horizontal Equivalent The horizontal distance between any two successive contours is called "Horizontal Equivalent".	01 M 01 M
	(ii) Ans.	Draw contour of Valley and Ridge line. 100 99 98 97 96 Valley line 97 98 99 100 Ridge line	01 M for each
	(iii) Ans.	State any four uses of transit theodolite. Following are the uses of transit theodolite. i) To measure horizontal angle. ii) To measure vertical angle. iii) To measure magnetic bearing of survey line. iv) To prolong a straight line.	1/2 M for each



	(iv)	Define the terms – Latitude and Departure.			
	Ans.	Latitude: Projection of survey line parallel to meridian is called as "Latitude".	01 M for		
	A.1.5.	Departure: Projection of survey line perpendicular to meridian is called as "Departure".	each		
	(v)	What is anallatic lens.	Cucii		
	Ans.	Additional lens provided in the telescope between the object glass and eye piece is known			
	711131	as "Annalatic lens". It eliminate constant (f+c) as the value of (f+c) when annalitic lens is provided is zero.			
	1				
	Ans.				
		1) Total Station			
		2) One Second Micro Optic Theodolite	Any four		
		3) Electronic Digital Theodolite	1/2 M		
		4) Digital level	for each		
		5) Remote Sensing			
		6) GPS			
		7) Aerial camera			
	(vii)	Define compound curve and reverse curve.			
	Ans.	Compound Curve: A compound curve consists of two arc of different radius curving in the			
		same direction. The centers of the two arc situated on the same side of the curve.	01 M for		
		Reverse Curve: A reverse curve consists of two arcs of equal or different radius curving in	each		
		opposite direction with a common tangent. The two centers are on the opposite sides of a			
		common tangent.			
	(viii)	Enlist type of curves used in road and railway alignment.			
	Ans.	Following are the curve used in road and railway alignment.			
		1. Horizontal Curve			
		i) Simple Curve ii) Compound Curve iii) Reverse Curve iv) Transition Curve v)	01 M		
		Lemniscates Curve			
		2. Vertical Curve			
		i) Summit Curve ii) Valley Curve	01 M		
Q.1	b)	Attempt any <u>TWO</u> of the following	(08)		
	(i)	State the methods of locating contours with merits and demerits of each.			
	Ans.	Following are the methods of locating contours			
		1) Direct Method			
		2) Indirect Method	02 M		
		i) By cross section ii) By Squares(Block Contouring) iii) Tachometric Method			
		Merits of Direct method :-			
		1) It gives accurate contour lines.	1/2 M		
		2) This method can be controlled from single Station.			
		Demerits of Direct method :-			
		1) This Method is Very Slow and tedious.	1/2 M		
		2) This method is applicable for small areas only.			
		Merits of Indirect method :-			
		1) This method is quicker and less tedious.	1/2 M		
		2) This method is applicable for large areas.			
		Demerits of Indirect method :-			



		1) It gives less accurate contour lines		1/2 M				
	(ii)	Describe layout of building using total star	tion.					
	Ans.	The procedure is as follows.						
		A) CENTERING THE TOTAL STATION:						
		·	e survey station to ensure that horizontal angle	01 M				
		observations are correct. The steps are as f						
			on. ii) Move the foot of tripod so that the optical					
			tation. iii) Roughly level the instrument using the					
		legs of the tripod the total station should s	tay almost on target.					
		B) LEVELLING THE TOTAL STATION 1) Turn hubble parallel to two foot serous	to bring the horizontal bubble to the centre of its	01 M				
		run by moving the foot screws in opposite directions (the bubble moves in the direction your left thumb).						
		ii) Turn the instrument through 90° and bring the bubble to the centre of its run by						
		adjusting the third foot screw only.	ing the bubble to the centre of its full by					
		,	0º to check the adjustment of the plate bubble.					
		s in adjusted position .						
			ement from the centre and re-adjust for a further					
		90º turn.						
		vi) Repeat the whole procedure; assuming	this is the correct, the bubble will stay in a					
		stationary position.						
		vii) The bubble must remain in the same place in the tube during a 360° rotation of the instrument.						
		viii) If the stationary position of the bubble	is still off the centre, then a permanent					
		adjustment should be made.						
		B) MARKING OF POINTS ON GROUND	::::					
			ifference between the desired distance and	02 M				
		making easier to locate exact points of layo	prism is held displayed by the total station					
			_					
	(iii)	(Note: Students may write the procedure using different command of total station) Differentiate between active system and passive system.						
	Ans.	Active System	Passive System					
		Autificial on ourse is used as a source	Nicture III. consists of a security is used as a					
		Artificial energy is used as a source	Naturally emitted energy is used as a source					
		In active system sensors are able to	In passive system sensors can obtain	01 M fo				
		obtain measurement anytime (day &	measurement in day time only	each				
		night)	measurement ady time only					
		Active system used their own source for	In passive system sensors can detect					
		illumination.	energy when the naturally occurring					
			energy is available					
		It is costlier	It is economical					
2.		Attempt any <u>FOUR</u> of the following		(16)				
	a)	Points 'P' and 'Q' are two ground points a	t a distance of 20 m with their reduced level are					
		75.380 and 78.260m respectively , interpolate the contours of 76, 77 and 78.						
	Ans.	Difference of level between P and Q = 78.2	60 -75.380 = 2.88 m in 20 m distance					
		To interpolate contours 76, 77 and 78 m.		01 M				



		Difference of level between P and 76 m contour point is 76 -75.380 = 0.62 m	
		Horizontal distance of 76 m contour from $P = 0.62 \times 20 / 2.88 = 4.31 \text{ m}$	01 M
		Difference of level between P and 77 m contour point is 77 -75.380 = 1.62 m	
		Horizontal distance of 77 m contour from $P = 1.62 \times 20 / 2.88 = 11.25 \text{ m}$	01 M
		Difference of level between P and 78 m contour point is 78 -75.380 = 2.62 m	
		Horizontal distance of 78 m contour from $P = 2.62 \times 20 / 2.88 = 18.19 \text{ m}$	01 M
		(Note :Students may write interpolation by estimation or graphical method appropriate	
		marks should be given for the above method also)	
Q.2	b)	Enlist uses of contour maps.	
	Ans.	Following are the applications of Contour map.	
		1. With the help of contour lines on contour map one can know the nature of ground.	
		2. For determination of most economical site for dams and reservoirs, maximum flood line,	
		submerged area.	Any four
		3. For estimating volume of water to be impounded in a reservoir.	01 M for
			each
		4. For location of highways, railways, canals, pipelines etc.	Cacii
		5. For determination of volume of cutting and embankment in given gradient.	
		6. For determining the indivisibility of two given points	
Q.2	c)	Calculate the area of figure in hectares, drawn to scale of 1 cm = 120 m, from following	
		data – I.R. = 2.695, F.R. = 9.148. Zero of dial passed the fixed index mark twice in clockwise	
		direction. Area corresponding to one revolution of roller is 100 sq. cm. Anchor point was	
		outside the figure.	
	Ans:		
		Given Data	
		scale of 1 cm = 120 m	
		I.R. = 2.695	
		F.R. = 9.148	
		Zero of dial passed the fixed index mark twice in clockwise direction	
		M = 100 sq. cm.	
		C = 0 (As Anchor point was outside the figure)	
		Solution:	
		Area A = M (F.R. – I.R. +10N + C)	01 M
		= 100 (9.148 - 2.695 + 10x2 + 0)	OT IVI
		= 2645.30 Sq. cm	
		Scale of area 1 cm = 120 m	04.54
		$1 \text{ cm}^2 = 120*120$	01 M
		Area of the field = $2645.30 \times 120 \times 120 = 38092.32 \times 10^3 \text{ Sq. m}$	
		Area of the field in hectares = $38092.32 \times 10^3/10000 = 3809.23$ hectares	01 M
			01 M
Q.2	d)	State any four uses of total station.	
	Ans.	Following are the uses of total station	
		1) Measurement of sloping distance.	
		2) Measurement of horizontal distance.	Any four
		3) Measurement of vertical distance.	01 M for
		4) Measurement of horizontal angle.	each
		5) Measurement of vertical angle.	
		6) Measurement of volume and area.	
		of Micasarement of Molame and area.	



Q.2	Ans. Tacheometry:						
	It is the branch of angular surveying in which horizontal distances from the instrument station to the staff station and the elevation of staff station are determined from the						
		instrumental observation only.	01 M				
		Principle of tachometry is based on principle of similar triangle in which corresponding sides					
		& altitudes are proportional. The ratio of distance of base from apex and length of base is	01 M				
		always Constant.					
		$a_2 b_2 c_2$					
		a, b, c,	01 M				
		minimo minimo					
		$D_1 \longrightarrow D_1$					
	In fig. O and O by O and are all increasing this makes whom D4 D2 D2 and the dist						
		In fig. $O_1a_1a_2$, $O_1b_1b_2$, $O_1c_1c_2$ are all isosceles triangles where D1, D2, D3 are the distances of bases from the apices and S1, S2, S3 are the Lengths of the bases.					
		According to stated principle.	01 M				
		D1/S1 = D2/S2 = D3/S3 = Constant	OI W				
		f/i= Multiplying constant.					
		f= Focal length of objective.					
		i= Stadia Intercept.					
Q.2	f)	Enlist the checks applied in case of closed traverse.					
	Ans.	Following are the checks applied in case of closed traverse a) Sum of measured included angles should be equal to (2N-4)x90					
		b) Sum of measured exterior angles should be equal to (2N-4)x90	01 M for				
		c) Algebric sum of deflection angle should be equal to 360° considering right hand	each				
		deflection angle as positive and left hand deflection angle as negative.					
		d) Summation of latitude and departure should be equal to zero.					
Q.3.		Attempt any <u>FOUR</u> of the following.	(16)				
	a)	State with sketch procedure for computing constants of planimeter.					
	Ans.	T					
		(H)	01 M				
			OT IAI				
		1 A J					



		Two cases are arise for computing constants of planimeter according to the position of the anchor	
		point.	03 M
		Case (1): Where the anchor point is outside the figure.	
		When the tracing arm the tracing arm returns to its original position, the pivot H oscillates along a	
		circular arc whose centre is A and returns to its position.	
		Total rotation of the tracing point about the pivot point is zero.	
		∫dƁ= 0	
		hence Δ= L _V	
		Now total rotation of the wheel	
		= algebraic sum of the arcs applied to the paper by the wheel	
		=nc	
		Whrere n = the number of revolutions made by the wheel	
		c= the circumference of the wheel = π .d	
		Therefore, Area of the figure= L_V	
		$= L_{cn} = L \times \pi.d \times n$	
		= M.n	
		The multiplier (M) = length of tracing arm x circumference of the wheel	
		$= L_c = L \times \pi.d$	
		Therefore, Area of the figure = $M(F.R-I.R \pm 10N)$	
		Case (2) When the anchor point is inside the figure.	
		In this case when tracing point is moved round the periphery of the figure, the tracing arm HT, and	
		also the pivot point H make a complete revolution when they return to their position. Therefore	
		$\int d^2B = 2\pi$. And the area (ΠR^2) of the circle. Hence	
		The area of the figure = $L_{nc} + \pi(L^2 + LL_1 + R^2)$	
		The quantity $\pi(L^2 + LL_1 + R^2)$ is known as the area of zero circle.	
		Then the area of the figure	
		$= M(F.R - I.R \pm 10N + C)$	
		, , , , , , , , , , , , , , , , , , ,	
		C is called the additive constant.	OR
		OR .	
		Draw the square or any regular area figure whose area A can be calculated by formula.	
		Keep anchor point outside and move the tracing arm clockwise. Take readings for IR, FR and N,	04 M
		put values in the formula and find the value of M , as $C = 0$.	04 101
		Now repeat the procedure keeping anchor point inside and putting values of IR, FR, N and M	
		find the value of C. (Note: For this procedure there is no need of sketch)	
Q.3	b)	State the component parts of micro optic theodolite. How it is superior to a transit	
		theodolite.	
	Ans.	Component parts of micro optic theodolite	
	/	1) Telescope	
		2) Magnification with standard eyepiece.	
		3) Level tube	
		4) Foot screws.	
			Any four
		5) Tribatch & Trivet	1/2 M
		6) Optical micrometer	for each
		7) Changing nob	101 00011
		8) Horizontal circle	
		9) Verticle circle.	
		Superior to Transit theodolite :	
		1) It is a recent development in surveying instrument which gives the 1" accuracy in measuring the	Any two
		angle.	01 M for
		2) This instrument is most suitable	each
		I.	55511



		3) This instrume 4) It is simple in	ent is durable for harsh environments. use.							
Q.3	c) Ans.	1 -	tic bearing of line AB is to be measured	_						
		 Set up the theodolite at A .Carry at all temporary adjustment centering and leveling properly. Set the vernier A at 000'00" and vernier 18000'00" using lower plate clamp, upper plate clamp and upper plate tangent screws. Fix the tabular circular or trough compass at its position on the theodolite (A standard of frame or on circular plate between the standards) and release the needle of the compass. Loosen the lower clamp, the telescope until its points to the north (i.e. magnetic needle coincides with the 0'-0' mark) which shows correct orientation of telescope along magnetic meridian. Fix the lower clamp and loosen the upper clamp, turn the telescope clockwise and bisect the ranging rod at B roughly. Fix the upper clamp; bisect the ranging rod at B correctly using upper tangent screw. Read both the vernier, the mean of these two vernier readings is the magnetic bearing of AB. 								
Q.3	d)	7) Change the face of the instrument repeat the above the procedure and measure the magnetic bearing of AB more precise. Differentiate between theodolite and tacheometer. Give any two characteristics of								
	Ans.	Sr.No.	Theodolite	Tacheometer						
		1	It is most accurate instrument use for	Tacheometer is usually a transit						
			measurement of horizontal and vertical angle.	theodolite having a stadia diaphragm.	Any two					
		2	In case of theodolite, the distance is measured on the field by chain or tape.	In case of tacheometer distance is calculated by direct formula.	01 M for each					
		3	Suitable for plane and hilly areas with less obstacles.	Suitable in case of obstruction like steep and broken ground.						
		4	More stations are required to take reading on field.	Less stations are required to take reading on field.						
		Characteristics of tacheometer — 1. The value of constant f/i = 100 2. The telescope should be powerful, the magnification should be 20 to 30 times the diameter 3. The telescope should be fitted with analytic lens to have the value of f +c = 0 4. The vision through the telescope should give a clear and bright image at a long distance.								



Q.3	e) Ans.	Draw net sketc	ch of simple circular curve showing all elements.			
	Alis.	When	Back Forward tangent	02 M for sketch and 02 M for labeling)		
		Where:	ant or roar tangent			
		BC = Forward ta	ent or rear tangent			
		T1 and T2 = Tan	-			
			int of intersection.			
		Δ = Deflection a				
		BD = External di	istance			
		T1T2 = Long cho				
		T1DT2 = Length				
Q.3	f) The interior angles of closed traverse ABCDE are as follows: <a 15″="" 18′="" 20″="" 220°="" 25′="" 30″="" 30″,="" 30″<="" 35′="" 40′="" 40″="" 45′="" 78°="" <b="104°" <c="85°" <d="150°" <e="120°" =="" ab="2200" ans:="" bearing="" calculate="" fb="" is="" line="" of="" remaining="" sides.="" th="" the="">					
		Add < B = 104°45′20″				
			325° 10′ 50″ 180° 0′ 00″			
		The FB of BC =	145° 10′ 50″	01 M		
		Add < C =	85° 35′ 40″			
		_	230°46′ 30″			
		Deduct	180° 0' 00"			
		The FB of CD =	50° 46′ 30″	01 M		
			150° 40′ 30″			
			201° 27′ 00″			
		Deduct	180° 0′ 00″	01 M		
		The FB of DE =		OT IVI		
		Add < E =	120° 18′ 15″			
		Bearing Of EA = Check,				
		Add < A =	78 ⁰ 40′ 15″			
		FB of AB =	220° 25′ 30″	01 M		



	Attempt any <u>FOUR</u> of the following.	(16)			
a) Ans.	Explain with example, establishing grade contours. In Establishing grade contour it is necessary to measure the distance from the starting point or the last point fixed to the next point to be fixed. The required staff reading is the calculated from i) the Distance ii) Given gradient iii) The R.L of plane of collimation of the level (HI).	02 M			
	Example : Suppose a down gradient of 1 in 25 is to be traced on the ground. Let RL of the starting point = 750.00 m .,The distance = 30 m, the height of instrument = 75.75 then R.L. of the next point = $750.00 - 30/25 = 750.00 - 1.2$ = 748.80 m H.I. = 750.75 m. There for the staff reading required at the next point = $750.75 - 748.80$ = 1.95 m.	02 M			
b)	State the errors that are eliminated by the method of repetition in the measurement of				
Ans.	 horizontal angle by transit theodolite. i) Errors due to eccentricity of verniers and centers are eliminated by taking the both readings ii) Errors due to in adjustments of line of collimation and trunnion axis are eliminated by taking both face readings. iii) Errors due to inaccurate graduations are eliminated by taking the readings at different parts of circle. 	01 M for each			
	iv) Errors due to inaccurate bisection of object, eccentric centering etc, may be some extent				
c) Ans:	Explain temporary adjustments of digital level. The following are the temporary adjustments: i) Setting up Tripod. ii) Centering. iii) Levelling iv) Focusing of object glass to remove the parallax. v) Initial setting procedure				
	 1. Setting up Tripod: Open the tripod legs sufficiently enough for the instrument to be stable. Assure that the station point is located directly beneath the center hole in the tripod below. Firmly press tripod shoes into the ground. Level the top surface of tripod head. 2. Centering: The centering can be performed either by plumb bob or optical plummet. Suspend the plumb bob from the hook provided at tripod mounting screw. Slightly loose the screw and carefully slide the instrument about tripod head, such that plumb bob is exactly over station point. 3. Levelling: Loosen the upper plate clamp, rotate the instrument and keep plate level parallel with any two levelling screws. Bring the plate bubble in the center by moving levelling screws. 	04 M			
	b) Ans.	a) Ans. Ans. Ans. In Establishing grade contour it is necessary to measure the distance from the starting point or the last point fixed to the next point to be fixed. The required staff reading is the calculated from i) the Distance ii) Given gradient iii) The R.L of plane of collimation of the level (HI). Example: Suppose a down gradient of 1 in 25 is to be traced on the ground. Let RL of the starting point = 750.00 m ., The distance = 30m, the height of instrument = 75.75 then R.L. of the next point = 750.00 – 30/25 = 750.00 – 1.2 = 748.80 m H.L. = 750.75 m. There for the staff reading required at the next point = 750.75 – 748.80 = 1.95 m. b) State the errors that are eliminated by the method of repetition in the measurement of horizontal angle by transit theodolite. Ans. i) Errors due to eccentricity of verniers and centers are eliminated by taking the both readings ii) Errors due to in adjustments of line of collimation and trunnion axis are eliminated by taking both face readings. iii) Errors due to inaccurate graduations are eliminated by taking the readings at different parts of circle. iv) Errors due to inaccurate bisection of object, eccentric centering etc, may be some extent counter-balanced in different observations. Explain temporary adjustments of digital level. The following are the temporary adjustments: i) Setting up Tripod. ii) Centering. iii) Levelling iv) Focusing of object glass to remove the parallax. v) Initial setting procedure 1. Setting up Tripod. • Open the tripod legs sufficiently enough for the instrument to be stable. • Assure that the station point is located directly beneath the center hole in the tripod below. • Firmly press tripod shoes into the ground. • Level the top surface of tripod head. 2. Centering: • The centering can be performed either by plumb bob or optical plummet. • Suspend the plumb bob from the hook provided at tripod mounting screw. • Slightly loose the screw and carefully slide the instrument about tripod head, such that plumb bob is exactly over station			

	1		
		center by third screw.	
		 Repeat the steps so that bubble remains in center for all positions. 	
		4. Removing /eliminating parallax:	
		Focusing eye piece and object glass eliminate the parallax.	
		5. Initial setting procedure:	
		Turn on the power switch	
		• Set minimum angle unit (5" or 10"); vertical 0° orientation with horizontal or zenith or	
		compass angle unit.	
		Automatic vertical compensation.	
		Automatic vertical compensation: Automatic power switch.	
0.4	۵۱	·	
Q.4	d)	Explain the setting of curve by Rankin's deflection angle method.	
	Ans.		
		First tangent $ \begin{array}{c ccccccccccccccccccccccccccccccccccc$	01 M for fig.
		1. Locate the tangent points T1 and T2 on the straight line AB and BC.	
		2.Set the theodolite at the beginning of the curve T1	
		3. With the vernier A of the horizontal circle set to zero, direct the telescope towards the	
		ranging rod at the point of intersection B and bisect it.	
		4. Unclamp the upper clamp screw and the vernier A to the first tangential angle ($\Delta 1$) and the	
		telescope being directed along T1P.	03 M for
		5. T1P the length equal to the first sub chord (C1) thus fixing point P on the curve.	procedur
		6. Set vernier A is equal to zero and direct the telescope toward the ranging rod fixed at the	e
		point of intersection B and bisects it.	6
		7. Unclamp the upper clamp screw and the vernier A to the second tangential angle (and the	
		telescope being directed along PQ.	
		8. With the zero end of chain or tape at P and with a arrow held at distance of PQ =C2 (second	
		chord or normal chord) swing the chin about P until the line sight bisect the arrow thus fixing	
		the second point Q on the curve.	
		9. Repeat the process until the last point T2 is reached.	
Q.4	e)	Explain the procedure for measuring vertical angle by using electronic theodolite.	
	Ans.	Suppose it is required to measure the vertical angle of an object 'P'	
		/ P	
			01 M
		O R	
	I		



		Procedu	ille.		1					
				instrument ov	ver statio	n 'O' and carry o	out all tempoi	arv adiustmen	ts	03 M
						w and direct the				05 141
			'P' exactly		P6 00. 0			TOTOLOGIA (PIGNIC		
		1		ing on display	ed windo	ow.				
Q.4	f)	State tl	he sources	of error in th	eodolite					
,	Áns.	1		of plate bubb						
		When t	he plate lev	els are cente	red the v	ertical axis may	not be truly v	ertical.		
		This wo	uld cause a	n error in ang	gle measu	rement.				
		ii. Line d	of collimation	on not being p	perpendic	ular to horizont	al axis.			Any four
		1			-	r to vertical axis				01 M for
		1				o axis of telesco	pe.			each
		1		ner and oute						
				eing uniform.						
		1	nier being e							
			•	ws may slip.						/>
Q.5			-	of the follo	_					(16)
	a)	Followi	ng are the	length of tro		d bearing of tr	averse.			
				Line	Length Meter	Kearina	9			
				AB	260 n					
				BC	325 n					
				CD	323 II 185 n					
		Fin d Ho	- lawath au			1 210				
		Find the length and bearing of line DA								
	Ans					Length in	Latitude	Departure		
			Line	Bearing	g	Meters	I*cosθ	I*sinθ		
			AB	30 ⁰		260	+225.16	+130.00		04 M
			BC	140 ⁰		325	-248.96	+208.90		
			CD	210 ⁰		185	-160.21	-92.50		
		-	<u> </u>			100	I*cosθ	l*sinθ		
			DA	θ (306° 50°	' 34")	? (306.88)	(+184.01)	(-245.59)		
		Since ABCDA is a closed traverse, $\Sigma L = 0$ and $\Sigma D = 0$								
		$\Sigma L = 0$								
			– 248.96 –	160.21 + lco	sθ = 0					
	$-184.01 + l\cos\theta = 0$									
	$Icos\theta = +184.01$								01 M	
		$\Sigma D = 0$								
		130 + 2	08.09 – 92	$.50 + lsin\theta = 0$	0					
		+245.59	$\theta + lsin\theta = 0$)						01.14
		lsinθ =	-245.59							01 M
		$ tan \theta = 1$	lsinθ/ Icos€	= 245.59/18	34.01 = 1.	335				
			-1 1.335	_						
		= 53.1	L57° = 53°	9′ 26″						
					is –ve, he	nce line lies in	IV quadrant.			01 M
			306° 50′ 34							OT IN
		Examin	ee should	give calculat	ion of lat	itude & depart	ture of each l	line.		
										go No 11/17



		Length of line DA = $$	$\sqrt{1^2 + D^2}$					
			$\sqrt{\frac{184.01^2 + 245.59^2}{184.01^2 + 245.59^2}}$					
						01 M		
0.5	h-1		06.88 m.	una cat un at station A	Land the fellowing			
Q.5	b)	readings were obtain		vas set up at station A Lstaff	ana the following			
		Inst. Station	Staff station	Vertical Angle	Stadia reading	7		
		A	BM	+8°	0.800, 1.120, 1.480	-		
		A	В	-4 ⁰	1.140, 1.235, 1.330	-		
			1		, ,	_		
		The constant (f/i) is 1	100, find distance AB	and RL of station B as	s RL of BM is 100.000 m.			
	Ans							
		Given -	(t/i) = 100;					
			R.L. of B.M = 10	5 1				
			V. C. OF D M = 10	U Mir.				
			Tackcometer fitted	With anallatic lens; Ct	f+d)=0			
		Con	1 10-9		1 3, -			
		Tine	d distance AB = { R:L: of B = : B = 40	* *	1,1			
			R.L. of B =	1200	3·M (100.000)			
		1 91.736	B-401	18=0	3,W (100,000)			
	Y2							
		1 32	A					
		h ₂						
		XH B						
		$S_1 = (1.480 - 0.800) =$	= 0.680			1/2 M		
		$\theta_1 = +8^0$				1/2 1/1		
		$h_1 = 1.120$						
		$V1 = (f/i)S1 (sin2 \theta_1)$ (f+d)=0						
		=100 X 0.68 X sin16/2	2 + 0					
		= 18.768/2				01 M		
		= 9.384 m						
		R.L. of instrument ax	is					
		$=$ R.L. of B.M. + $h_1 - V$	1					
		= 100 + 1.120 - 9.384				01 M		
		= 91.736 m						
		$S_2 = (1.330 - 1.140)$						
		= 0.190				1/2 M		
		$\Theta_2 = 4^0$						
		$h_2 = 1.235$	2) . (5 !) -: 2					
		$V_2 = (f/i) S_2 X (sin 2\theta_2 / extends)$				01 M		
		= 100 X 0.190 X (sir	10/2)+0			01 141		
		V_2 = 1.320 m RL of station B						
1			ment axis – V_2 – h_2					



	ı							
		= 91	736 – 1.320 – 1.235		02 M			
		= 89.181 m						
		$L(AB) = (f/i)S_2X \cos^2\theta_2 + (f+d) \cos\theta_2$						
		= 100 X 0.190 X 0.995						
		= 18.905 m						
		R.L. of station point B = 89.181 m						
		L(AB) = 18.905 m						
Q.5	c)i)	Differentiate between Prismoidal formula and trapezoidal formula for computation of volume.						
	Ans	SR.NO.	TRAPEZOIDAL	PRISMOIDAL				
			Volume is calculated as –	Volume is calculated as -				
			V=common distance/2 X (area of	V= common distance/3 X (area of first				
		1	first section + area of last section) +	section + area of last section) + 4(sum				
			2(sum of area of other section)	of areas of even section + 2(sum of				
			,	areas of odd section)				
			This gives approximate volume.	It gives accurate volume.				
		2	This gives approximate volume.	regives accurate volume.	Any four			
			There is no limitations. It can be	Prismoidal formula is applicable when	01 M for			
		3	applied for any number of areas	there are odd number of section	each			
			(even or odd)	there are out frammer of section				
			The boundaries between the ends	The boundaries between ends of				
		4	of ordinates are assumed to be	ordinates are assumed tobe arc of				
		-	straight.	parabola.				
			No need of separation of areas.	If number of areas are even the end				
			No fleed of separation of areas.	strip is treated separately & area is				
		5		calculated according to trapezoidal rule.				
				The volume of remaining strip is				
				calculated by prismoidal formula & both				
				volumes are added to get final volume.				
0.5	- \\	Ctoto the o	adventage and discolumntage of CDC					
Q.5	c)ii)		dvantages and disadvantages of GPS	•				
	Ans	Advantage						
		,	elps to survey with many times greater	•				
		2) It helps to complete survey in lesser time & thus help in reducing completion period.						
		3) It helps reduces the difficulty of taking manual measurement to great extent.						
		4) Chances of errors are less. Error may occur due to instrument malfunction.						
		ı '	S works in all weather conditions.		A			
		· ·		mineral exploration, wild life habitation	Any four 1/2 M			
		7) It helps in search & rescue operation.						
		8) It gives latitude & longitude of a point.						
		9) It keeps record of tracking.						
				d design of placement. One can select the				
		· ·	imum measurement points.					
		11) It improves mapping as well as tracking skill.						
		12) GPS is extremely easy to navigate.						
i .	1	Disadvanta	ages.					



1) It requires high initial investment. 2) It requires much skilled person to operate. 3) GPS may fail due to certain reason & therefore need to carry a backup maps & directions. 4) GPS works only where satellite signals & reception is possible. 5) It completely relies on receiving signals. 6) GPS signals are not accurate due to obstacles. Consecutive coordinates for the following observations of traverse.		1											
3) GPS may fail due to certain reason & therefore need to carry a backup maps & directions. 4) GPS works only where satellite signals & reception is possible. 5) It completely relies on receiving signals. 6) GPS signals are not accurate due to obstacles. Consecutive coordinates for the following observations of traverse.			1	•	_								
Ans Calculate the corrected consecutive co-ordinates for the following observations of traverse.		2) It requires much skilled person to operate.									Any four		
A) GPS works only where satellite signals & reception is possible. 5) It completely relies on receiving signals. 6) GPS signals are not accurate due to obstacles. Calculate the corrected consecutive co-ordinates for the following observations of traverse. Line			3)	GPS may	fail due	to certain r	eason & the	refore nee	d to carry a	a backup m	iaps &	1/2 M	
S It completely relies on receiving signals. 6 GPS signals are not accurate due to obstacles.				directio	ns.							for each	
S It completely relies on receiving signals. 6 GPS signals are not accurate due to obstacles.			4)	GPS wor	ks only w	here satell	ite signals &	reception i	is possible.				
Calculate the corrected consecutive co-ordinates for the following observations of traverse. Line			1		-		_	·	·				
Q.5 a) Calculate the corrected consecutive co-ordinates for the following observations of traverse. Line Length (m) Point Lotitude Departure AB 705 A +655.19 -260.29 BC 952.5 B +127.07 +943.99 CD 645 C -628.47 +145.54 DA 844.5 D -151.48 -830.80 LINE LENGT H (M) AB 705 A +655.19 -260.29 -0.517 +0.349 654.67 -259.94 BC 952.5 B +127.07 +943.99 -0.699 +0.472 126.37 +944.462 CD 645 C -628.47 +145.54 -0.473 +0.319 -628.94 +145.859 DA 844.5 D -151.48 -830.80 -0.620 +0.418 -152.10 -830.382 3147.0 \$\frac{1}{2}\$ Le \$\frac{1}{2}\$ D = \$\frac{1}{2}\$ Le \$\frac{1}{2}\$ D = \$\frac{1}{2}\$ Le = \$\frac{1}{2}\$ Le = \$\frac{1}{2}\$ D = \$\frac{1}{2}\$ Le = \$\frac{1}{2}\$ Le = \$\frac{1}{2}\$ Le = \$\frac{1}{2}\$ Le =			1	-	-			acles.					
Line Length (m) Point Consecutive coordinates													
Line Length (m) Point Consecutive coordinates													
Line	Q.6	a)	Calculate the corrected consecutive co-ordinates for the following observations of										
Line Length (m) Point Latitude Departure			traverse.										
Line Length (m) Point Latitude Departure													
Ans Latitude Departure								Cor	nsecutive c	o-			
Ans AB			Line		Lengtl	h (m)	Point	ordinates					
Ans BC 952.5 B +127.07 +943.99								Latitud	Latitude Dep				
Ans LINE LENGT POINT CONSECUTIVE CO-ORDINATES CORRECTION CORRECTED CONSECUTIVE CO-ORDINATES L D L D L D L D L D L D L D L D L D L				AB	70	5	Α	+655.19 -2		50.29			
Ans Line Lengt Point Consecutive Co-Ordinates Consecutive Co-Ordinates				ВС	952	2.5	В	+127.0	07 +94	13.99			
Line Lengt				CD	64	5			17 +14	15.54			
LINE LENGT POINT CONSECUTIVE CO-ORDINATES CORRECTION CORRECTED CONSECUTIVE CO-ORDINATES				DA	844	1.5	D	-151.48	18 -83	80.80			
H (M) ORDINATES CONSECUTIVE COORDINATES		Ans											
H (M) ORDINATES CONSECUTIVE COORDINATES			LINE	LENGT	POINT			CORRECT	CORRECTION		TED		
Name					T Ont			Co					
L D L D L D D D D D D D D D D D D D D													
AB 705 A +655.19 -260.29 -0.517 +0.349 654.67 -259.94 BC 952.5 B +127.07 +943.99 -0.699 +0.472 126.37 +944.462 CD 645 C -628.47 +145.54 -0.473 +0.319 -628.94 +145.859 DA 844.5 D -151.48 -830.80 -0.620 +0.418 -152.10 -830.382 3147.0 \(\subseteq \textsup L = \subseteq \textsup D = \subseteq \textsup L = \subseteq \textsup D = \subseteq \textsup L = 00 \subseteq \textsup D = 00 \\						1	D	1					
BC 952.5 B +127.07 +943.99 -0.699 +0.472 126.37 +944.462 CD 645 C -628.47 +145.54 -0.473 +0.319 -628.94 +145.859 DA 844.5 D -151.48 -830.80 -0.620 +0.418 -152.10 -830.382 3147.0 ∑L = ∑D = ∑L = ∑D = ∑L = OD ∑D = 00 BOWDITCH RULE 1) Correction to latitude of any side. = (length of that side / perimeter of traverse) X total error in latitude. 2) Correction in departure of any side. = (length of that side / perimeter of traverse) X total error in departure. Correction to latitude 1) Correction to latitude of line AB = (705/3147) X 2.31 = -0.517 2) Correction to latitude of line BC = (952.5/3147) X 2.31 = -0.699 3) Correction to latitude of line CD = (645/3147) X 2.31 = -0.473			ΔR	705	Δ				_				
CD 645 C -628.47 +145.54 -0.473 +0.319 -628.94 +145.859 DA 844.5 D -151.48 -830.80 -0.620 +0.418 -152.10 -830.382 3147.0 Σ L = Σ D = Σ L = Σ D = Σ L = 00 Σ D = 00 + 2.31 -1.56 -2.31 +1.56 BOWDITCH RULE 1) Correction to latitude of any side. = (length of that side / perimeter of traverse) X total error in latitude. 2) Correction in departure of any side. = (length of that side / perimeter of traverse) X total error in departure. Correction to latitude 1) Correction to latitude of line AB = (705/3147) X 2.31 = -0.517 2) Correction to latitude of line BC = (952.5/3147) X 2.31 = -0.699 3) Correction to latitude of line CD = (645/3147) X 2.31 = -0.473							+			_			
DA 844.5 D -151.48 -830.80 -0.620 +0.418 -152.10 -830.382 3147.0				+					_	+			
3147.0 \[\begin{array}{cccccccccccccccccccccccccccccccccccc							+		_	+		04 M	
BOWDITCH RULE 1) Correction to latitude of any side. = (length of that side / perimeter of traverse) X total error in latitude. 2) Correction in departure of any side. = (length of that side / perimeter of traverse) X total error in departure. Correction to latitude 1) Correction to latitude of line AB = (705/3147) X 2.31 = - 0.517 2) Correction to latitude of line BC = (952.5/3147) X 2.31 = - 0.699 3) Correction to latitude of line CD = (645/3147) X 2.31 = - 0.473			DA	+	D				_	+			
BOWDITCH RULE 1) Correction to latitude of any side. =(length of that side / perimeter of traverse) X total error in latitude. 2) Correction in departure of any side. =(length of that side / perimeter of traverse) X total error in departure. Correction to latitude 1) Correction to latitude of line AB = (705/3147) X 2.31 = - 0.517 2) Correction to latitude of line BC = (952.5/3147) X 2.31 = - 0.699 3) Correction to latitude of line CD = (645/3147) X 2.31 = - 0.473				3147.0		l —	-	_	I —	∑ r =00	> D = 00		
1) Correction to latitude of any side. =(length of that side / perimeter of traverse) X total error in latitude. 2) Correction in departure of any side. =(length of that side / perimeter of traverse) X total error in departure. Correction to latitude 1) Correction to latitude of line AB = (705/3147) X 2.31 = - 0.517 2) Correction to latitude of line BC = (952.5/3147) X 2.31 = - 0.699 3) Correction to latitude of line CD = (645/3147) X 2.31 = - 0.473				D 0) 4 / D I T	011 0111 0	+ 2.31	- 1.56	- 2.31	+ 1.56				
= (length of that side / perimeter of traverse) X total error in latitude. 2) Correction in departure of any side. = (length of that side / perimeter of traverse) X total error in departure. Correction to latitude 1) Correction to latitude of line AB = (705/3147) X 2.31 = - 0.517 2) Correction to latitude of line BC = (952.5/3147) X 2.31 = - 0.699 3) Correction to latitude of line CD = (645/3147) X 2.31 = - 0.473				ROMDII	CH RULE								
= (length of that side / perimeter of traverse) X total error in latitude. 2) Correction in departure of any side. = (length of that side / perimeter of traverse) X total error in departure. Correction to latitude 1) Correction to latitude of line AB = (705/3147) X 2.31 = - 0.517 2) Correction to latitude of line BC = (952.5/3147) X 2.31 = - 0.699 3) Correction to latitude of line CD = (645/3147) X 2.31 = - 0.473													
2) Correction in departure of any side. =(length of that side / perimeter of traverse) X total error in departure. Correction to latitude 1) Correction to latitude of line AB = (705/3147) X 2.31 = - 0.517 2) Correction to latitude of line BC = (952.5/3147) X 2.31 = - 0.699 3) Correction to latitude of line CD = (645/3147) X 2.31 = - 0.473			1)			•							
= (length of that side / perimeter of traverse) X total error in departure. Correction to latitude 1) Correction to latitude of line AB = (705/3147) X 2.31 = - 0.517 2) Correction to latitude of line BC = (952.5/3147) X 2.31 = - 0.699 3) Correction to latitude of line CD = (645/3147) X 2.31 = - 0.473			_,					erse) X tota	al error in I	atitude.			
Correction to latitude 1) Correction to latitude of line AB = (705/3147) X 2.31 = - 0.517 2) Correction to latitude of line BC = (952.5/3147) X 2.31 = - 0.699 3) Correction to latitude of line CD = (645/3147) X 2.31 = - 0.473			· · · · · · · · · · · · · · · · · · ·										
1) Correction to latitude of line AB = (705/3147) X 2.31 = - 0.517 2) Correction to latitude of line BC = (952.5/3147) X 2.31 = - 0.699 3) Correction to latitude of line CD = (645/3147) X 2.31 = - 0.473													
= (705/3147) X 2.31 = - 0.517 2) Correction to latitude of line BC = (952.5/3147) X 2.31 = - 0.699 3) Correction to latitude of line CD = (645/3147) X 2.31 = - 0.473													
= - 0.517 2) Correction to latitude of line BC = (952.5/3147) X 2.31 = - 0.699 3) Correction to latitude of line CD = (645/3147) X 2.31 = - 0.473			1)				AB						
2) Correction to latitude of line BC = (952.5/3147) X 2.31 = - 0.699 3) Correction to latitude of line CD = (645/3147) X 2.31 = - 0.473					•	31							
= (952.5/3147) X 2.31 = - 0.699 3) Correction to latitude of line CD = (645/3147) X 2.31 = - 0.473			_,										
= - 0.699 3) Correction to latitude of line CD = (645/3147) X 2.31 = - 0.473			2)				ВС						
3) Correction to latitude of line CD = (645/3147) X 2.31 = - 0.473				-		2.31							
= (645/3147) X 2.31 = - 0.473													
= - 0.473			3)				CD						
				-		31							
4) Correction to latitude of line DA													
			4)	Correction	on to latit	tude of line	DA						



		= (844.5/3147) X 2.31				
		= - 0.620				
		{ error is +ve, correction will be –ve}				
		Correction to departure				
		1) Correction to departure of line AB				
		= 705/3147 X 1.56 = +0.349	02 M			
		2) Correction to departure of line BC				
		=952.5/3147 X 1.56 = +0.472				
		3) Correction to departure of line CD				
		=645/3147 X 1.56 = +0.319				
		4) Correction to departure of line DA				
		=844.5/3147 X 1.56 = +0.418				
		[error is -ve, correction will be +ve]				
Q.6	b)	Calculate the ordinates of 25m interval to set out a circular curve having a long chord				
		300m and versed sine of 10m.				
	Ans	Given-				
		1) Peg interval – 25m				
		2) Length of long chord – 300 m				
		3) Versed sine – 10 m				
		Versed sine = $O_0 = R - \sqrt{R^2 - (L/2)^2}$				
		R = ?				
		L/2 = 300/2 = 150 m				
		$O_0 = 10 \text{ m}$				
		$10 = R - \sqrt{R^2 - (L/2)^2}$				
		$(10 - R) = -\sqrt{R^2 - (L/2)^2}$ (1)				
		Squaring equation (1) on both sides.				
		$(10-R)^2 = R^2 - (L/2)^2$				
		$(10-R)^2 = R^2 - (150)^2$				
		$100 - 20R + R^2 = -22500 + R^2$				
		20R = 22600				
		R = 1130 m				
		O ₀ = 10 m	01 M			
		$O_{25} = \sqrt{R^2 - (25)^2} - (R - O_0)$				
		$= \sqrt{(1130)^2 - 625} - (1130 - 10)$				
		=9.72 m				
			01 M			
		$O_{50} = \sqrt{(1130)^2 - 2500} - 1120$				
		=8.89 m				
			01 M			
		$O_{75} = \sqrt{(1130)^2 - (75)^2 - 1120}$				
		=7.51 m	01 M			
			1			



	T		1					
		$O_{100} = \sqrt{(1130)^2 - (100)^2 - 1120}$ =5.57 m	01 M					
		$O_{125} = \sqrt{(1130)^2 - (125)^2 - 1120}$ =3.065 m						
		$O_{150} = \sqrt{(1130)^2 - (150)^2 - 1120}$ = 0.00 m						
		2 0, 3,085 5,57 7,51 8,89 9,72 10 1,50 100 100	01 M					
Q.6	c) Ans	 State the procedure of traversing by using total station. Procedure of traversing using total station. Set up total station over station point, the co-ordinates of which are known or fixed arbitrarily. Carry out proper centering & leveling. Create a file in T.S. where particular traverse survey data will be saved. Now go to 'meas' & input co-ordinate details of station point(point no.,N,E,Z,PC,ZH) Then input 'BSP'(basic sight point) details in the first station only. 'Azimuth' or initial bearing (0°0°0°) & entered. New point in the telescope of T.S. towards B.S.P., bisect the target & press enter. Then go to 'rectangular co-ordinate' & measure the BSP. It displays the co-ordinate of BSP generated in accordance station point. This form the orientation or basis of entire traverse survey. Now save the BSP. Point telescope towards the foresight bisect the same properly. Measure the third point in similar manner, measured co-ordinates(P.no,N,E,Z) is now displayed. Edit & input 'PC' & "PH" details & save data. Now remove instrument from the initial station & set up like earlier over the foresight point, whose co-ordinates are just measured by T.S. Carry out temporary adjustment. Input co-ordinate data or select from the list. Aim at 	08 M for correct steps					



(Autonomous) (ISO/IEC - 27001 - 2013 Certified)

BSP & take measurement. The screen displays measured co-ordinates of BSP. If it is within tolerance + / - less tha 5° it is ascertained as good reference.

- 12) Now point telescope towards next point. Bisect it & then measure. Edit & input "PC" & then save the data.
- 13) In closed traverse after measuring the initial or starting point if closing error is found it is processed by software

